



## I-87017DW-G

8-channel Differential/16-channel Single-Ended Analog Input Module with High Voltage Protection

#### **■** Introduction

The I-87017DW is a 8-channel differential/16-channel single-ended analog input module. The analog input range is software selectable and supports  $\pm 10$  V,  $\pm 5$  V,  $\pm 1$  V,  $\pm 500$  mV,  $\pm 150$  mV,  $0 \sim +20$  mA, +4  $\sim$  +20 mA,  $\,$  and ±20 mA. And all channels support 240 Vrms overvoltage protection in differential mode. Differential mode and single-ended mode is selected via jumper selectable jumpers.

#### Applications

- Building Automation
- Factory Automation
- Machine Automation
- Remote Maintenance
- Remote Diagnosis
- Testing Equipment

# **■ System Specifications**

Communication			
Interface	RS-485		
Format	N, 8, 1		
Baud Rate	1200 to 115200 bps		
Protocol	DCON		
Dual Watchdog	Yes, Module (1.6 Seconds), Communication (Programmable)		
LED Indicators/Display			
System LED Indictors	Yes, 1 as Power/Communication Indicator		
I/O LED Indicators	16 as High/Low Alarm Signals		
Isolation			
Intra-module Isolation, Field-to-Logic	3000 VDC		
EMS Protection			
ESD (IEC 61000-4-2)	±4 kV Contact for each Terminal		
ESD (IEC 01000-4-2)	±8 kV Air for Random Point		
Power			
Power Consumption	1.3 W Max.		
Mechanical			
Dimensions (W × L × H)	30 mm × 114 mm × 85 mm		
Environment			
Operating Temperature	-25 to +75°C		
Storage Temperature	-40 to +85°C		
Humidity	10 to 95% RH, Non-condensing		

#### **₱** Features

- 8-channel Differential/16-channel Single-ended Analog Input
- D-Sub 37-Pin Connector
- 4 kV ESD Protection
- Dual Watchdog
- 3000 V<sub>DC</sub> Intra-module Isolation, Field-to-Logic











I-8017DW, I-8040W, I-8040PW, I-8041W, I-8041AW, I-8041PW, I-8042W, I-87017DW, I-87024DW, I-87028CDW, I-87040W, I-87040PW, I-87041W, I-87041PW and I-87042W with DN-37-381-A & DB37 Male to Female Cable (Optional)


## **■ I/O Specifications**

Analog Input				
Channels		8 Differential or 16 Single-ended, (See Note 1), Jumper Selectable		
Range		$\pm 10$ VDC, $\pm 5$ VDC, $\pm 1$ VDC, $\pm 500$ mV, $\pm 150$ mV, $0 \sim +20$ mA, $+4 \sim +20$ mA, $-20$ mA $\sim +20$ mA (Requires Optional External 125 $\Omega$ Resistor)		
Resolution	Normal Mode	16-bit		
Resolution	Fast Mode	12-bit		
Accuracy	Normal Mode	±0.1% of FSR		
Accuracy	Fast Mode	±0.5% of FSR		
Sampling	Normal Mode	16-bit, 10 Hz (Total)		
Rate	Fast Mode	12-bit, 50 Hz (Total)		
-3dB Bandwidth		15.7 Hz		
Zero Drift		±20 μV/°C		
Span Drift		±25 ppm/°C		
Common Mode Rejection		86 dB		
Normal Mode Rejection		100 dB		
Townsh Towns			2 ΜΩ	
Input Impedance		Single-ended	1 ΜΩ	
Individual Channel Configurable		Yes		
Open Daughter Board Detection		Yes		
Overvoltage Protection		Differential	240 Vrms	
		Single-ended	150 Vrms	


Note 1: Differential mode can be used for voltage input and current input. Single-Ended mode can be used for voltage input only.

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2020.12 1/2

## **■ Internal I/O Structure**



## **■** Dimensions (Units: mm)




#### **■ Wire Connections**

Input Type	Differential	Single-ended
JP4 Jumper		
Voltage Input Wiring	mV/V U □ Vin+ Vin-	mV/V U U Vin AGND
Current Input Wiring	125Ω   Vin+ Vin-	Vin αGND
Note: When connecting to a current source, an optional external $125\Omega$ resistor is required.		

Daughter Board Detection			
Connect	Open		
□	□⊜ BK+ □⊜ BK-		

## **■ Pin Assignments**



Pin Assignment	Terminal	0	No.	Pin Assignment
AGND	19	0	37	BK+
AGND	18	• •		
V7-/V15+	17	•	36	N/A
V7+	16	•	35	N/A
V6-/V14+	15	•	34	N/A
V6+	14	•	33	N/A
V5-/V13+	13	•	32	N/A
V5+	12	•	31	N/A
V4-/V12+	11	•	30	N/A
V4+	10	•	29	N/A
V3-/V11+	09	•	28	N/A
V3+	08	•	27	N/A
V2-/V10+	07	• •	26	N/A
V2+	06	• •	25	N/A
V1-/V9+	05	• •	24	N/A
V1+	04	• •	23	N/A
V0-/V8+	03	• •	22	N/A
V0+	02	• •	21	N/A
BK-	01		20	N/A
		O		in Male ıb Connector

## **■** Ordering Information

I-87017DW-G CR

8/16-ch AI Module with High Overvoltage Protection (Gray Cover) (RoHS)
Includes CA-4002F (DB37 connector Female with plastic cover)

#### Accessories

-em-	2AB125R	125 $\Omega$ , 0.1% DIP Resistor used for Current Type Input Modules
	DN-37-A CR	Female DB37 to Screw Terminal Board (Pitch= 5.08 mm) with DIN-rail Mounting (RoHS) Include: CA-3710A (DB37 Male to Female Cable, 90°, 1 M)
	DN-37-381-A CR	Female DB37 to Screw Terminal Board (Pitch=3.81 mm) with DIN-rail Mounting (RoHS) Include: CA-3710A (DB37 Male to Female Cable, 90°, 1 M)
53	CA-3705A CR CA-3710A CR CA-3715A CR	DB37 Male to Female Cable, 90°, 0.5 M/1 M/1.5 M (RoHS)
	CA-3710AM CR CA-3720AM CR CA-3730AM CR CA-3750AM CR CA-37100AM CR	DB37 Male to Female, with Molded Cable, 45°, 1 M/2 M/3 M/5 M/10 M (RoHS)

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2020.12 2/2