



I-87054W-G

8-channel Isolated Digital Input and 8-channel Isolated Digital Output Module

■ Introduction

The I-87054W module offers 8 isolated Digital Input channels and 8 isolated Digital Output channels. Either sink- or source-type Digital Input can be selected via the wire connections, and all Digital Input channels are also able to be used as 16-bit counters. The I-87054W supports sink-type output with short circuit protection. The I-87054W includes 16 LED indicators that can be used to monitor the status of the Digital Input and Digital Output channels, and options are available for configuring both power-on and safe values. 4 kV ESD protection and 3750 VDC intra-module isolation are provided as standard.

■ Features

- 8-channel Isolated Digital Input and 8-channel Isolated Digital Output
- Sink-type Digital Output Channels with Overload Protection
- All Digital Input Channels can be used as 16-bit Counters
- Short-circuit and Overcurrent Protection
- 4 kV ESD Protection
- 3750 V_{DC} Intra-module Isolation
- Configurable Power-on Value
- Configurable Safe Value
- RoHS Compliant
- Wide Operating Temperature Range: -25 to +75°C









Applications

- $\bullet \ \text{Building Automation}$
- Factory Automation
- Machine Automation
- Remote Maintenance
- Remote Diagnosis
- Testing Equipment

System Specifications


incacions		
Communication		
RS-485		
N, 8, 1		
1200 to 115200 bps		
DCON		
Yes, Module (1.6 Seconds), Communication (Programmable)		
1		
Yes, 1 as Power/Communication Indicator		
16 as High/Low Alarm Signals		
3750 Vrms		
EMS Protection		
±4 kV Contact for each Terminal		
±8 kV Air for Random Point		
0.7 W Max.		
115 mm × 30 mm × 102 mm		
-25 to +75°C		
-40 to +85°C		
10 to 95% RH, Non-condensing		

■ I/O Specifications


_	peemeations	
Digital Inp	ut	
Channels		8
Туре		Wet Contact
Sink/Source (NPN/PNP)		Sink, Source
ON Voltage Level		+3.5 VDC ~ +50 VDC
OFF Voltage Level		+1 VDC Max.
Input Imped	ance	10 kΩ, 0.66 W
	Channels	8
Carratana	Max. Count	16-bit (65535)
Counters	Max. Input Frequency	100 Hz
	Min. Pulse Width	5 ms
Channel-to-C	Channel Isolation	Yes
Low Pass Filt	ter	Yes
Effective Distance for Dry Contact		-
Digital Out	put	
Channels		8
Туре		Open Collector
Sink/Source	(NPN/PNP)	Sink
Load Voltage		+5 VDC ~ +50 VDC
Max. Load Current		700 mA/channel
Overvoltage Protection		60 VDC
Overload Protection		Yes
Short-circuit and Overcurrent Protection		Yes, 1.4 A
Power-on Value		Yes
Safe Value		Yes

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2019.11 1/2

■ Internal I/O Structure



■ Dimensions (Units: mm)




■ Wire Connections

Digital ON State Input/ Readback as 1		OFF State Readback as 0
	OPEN or < +1 VDC	+4 ~ +30 VDC
Sink	× DIx 10kΩ + - To other channels	→ DIx 10kΩ → To other channels
	OPEN or < +1 VDC	+4 ~ +30 VDC
Source	× DIx 10kΩ - + To other DI.COM : channels	C DIX 10kΩ To other channels

Output Type	ON State Readback as 1	OFF State Readback as 0
Digital Output (Resistance Load)	DOX DO.PWR DO.GND	× I Load □ □ □ DOx DO.PWR □ □ DO.GND
Digital Output (Inductive Load)	DOX DO.PWR DO.GND	×

Pin Assignments



Ter	minal No.	Pin Assignment
	01	DI.COM
	02	DI0
[n (03	DI1
	04	DI2
5-0	05	DI3
	06	DI4
F = (07	DI5
	08	DI6
	09	DI7
5 - (10	DO0
	11	DO1
	12	DO2
C B	13	DO3
	14	DO4
	15	DO5
	16	DO6
	17	D07
	18	DO.GND
	19	DO.GND
	20	DO.PWR

■ Ordering Information

1-87054W-G 8-channel Isolated Digital Input and 8-channel Isolated Digital Output Module using the DCON Protocol (Gray Cover) (RoHS)

Accessories

RM-104/108/116	4/8/16-channel 16 A Power Relay Board, 1 Form C	
RM-204/208/216	4/8/16-channel 8 A Power Relay Board, 2 Form C	
DN-SSR4	4-channel 1A Solid-state Relay Board, 1 Form A	

RM-22.22	1-channel 20 A Power Relay for Direct 35 mm Rail (EN 50022) Mounting, 2 Form A
SG-770 CR	7-channel Differential or 14-channel Single-ended Surge Protector (RoHS)

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2019.11 2/2